

*Journe*  
air1000

**Digital Photo Frame**

Digital wireless photo frame with internet radio and remote control.



> **WATCH YOUR PICTURES AS IF YOU WERE AT THE MOVIES**

Enjoy in full comfort the 10" (25.4 cm) 16:9 LCD TFT screen and its bright, crystal clear colours

> **MORE THAN JUST A PICTURE FRAME**

This multimedia player feature an IP radio with 30 to 50 preset channels

> **NO WIRES, NO LIMITS**

The integrated wireless module allows direct, easy connection to RSS feeds or to your Flickr® or Picasa® albums

> **A CONTINUOUS DISCOVERY, PICTURE BY PICTURE**

Battery, tilt sensor, remote control. The air1000 never stops surprising you

*Journe*  
Memories in motion

[www.toshiba-multimedia.com](http://www.toshiba-multimedia.com)

Journe air1000  
PA3699E-1ET1 (EU), PA3699D-1ET1 (UK),  
PA3699M-1E1 (EMEA)



An intuitive remote control guarantees full access to all the functions and features of this device.

## > BASIC SPECIFICATION

Panel Type:	LED backlight panel
Panel Size:	10.1" (25.65 cm) 16:9 800 (W) x 480 (V)
Brightness:	180 nits (5 levels adjustable)
Contrast:	400:1
Viewing Angle:	45 / 65 / 65 / 65 degree (Top / Bottom / Left / Right)
Power Supply:	AC/DC power adaptor (9V / 2A)
Battery:	Internal 1800 mAh Li-polymer battery (30 minutes)
Sensor:	Partial touch and Tilt sensor
Memory Cards Support:	Slot-1: SD*, MMC, MS and MS Pro, xD (*SDHC: supported up to 32GB) Slot-2: CF card
Internal Memory:	1GB NAND Flash
Supported File Format:	Pictures: JPEG, BMP Audio: MP3, WMA Video: Motion JPEG (.AVI, .MOV)
Converting Software:	Convert Audio/Video file to a different (compression) format
Converting format includes:	Audio: MP3, AAC, OGG (TBD) Video: Motion JPEG, MPEG 4, WMV, H.263, H.264 (TBD)
Speaker:	0.5 W Speaker*2 (stereo)
USB port:	1. A type-Female USB 1.1 (Host) 2. Mini-B-Female USB 2.0 (USB device)
Adaptor:	Universal, Output: 9V/2A
Dimensions (mm):	264.57 (L) x 167.73 (W) x 32.8 (Thickness) [Without Stand]
Weight (g):	745 g (With Stand)

## > MAIN FEATURES

- 10.1" (25.65 cm) display - 16:9 (800 x 480 resolution)
- Partial touch design in display panel
- Wi-Fi (802.11 b/g)
- IP radio with 30-50 default channels
- Auto file re-sizing
- Converting Software (Audio/Video conversion SW)
- Battery, Tilt Sensor
- IR with remote control

## > FUNCTIONAL MODES

- Thumbnails
- Slide Show (with Transition effect)
- Audio Playback
- Video Playback
- Calendar, Clock, Alarm
- Timer mode (for auto power on/off)
- IP Radio Mode (Access to „SHOUTcast” protocol, with 30-50 default channels)
- Wi-Fi model (with linkage to Flickr, Picasa and RSS reader)

## > BOX CONTENT

- Journe air1000 & Stand
- USB cable (90 cm)
- AC adaptor
- Quick Start Guide
- CD with software & User's Manual

## > SYSTEM REQUIREMENTS

- Microsoft® Windows® 2000/XP/Vista®
- CPU: 1 GHz+
- RAM: 512 MB+
- HD Space: 200 MB+
- Video RAM: 64 MB+

## > CERTIFICATIONS

WEEE, CE, GOST, SASO, SABS

Dealer stamp: